Solar Power Generator

Awesome for camping,emergency power outage places or disaster areas.

& LG cell inside

PS-100

Features:

- 1. This unit has a built-in pure-sine wave inverter that provides the quietpower.
- 2. LED Light: With flash light and QC3.0 function.
- 3. Two Charging Ways: It allowed to be charged by solar panel, or adapter.
- 4. Battery Management System(BMS): BMS conducts active cell balancing to optimize battery performance and longer battery life.
- 5. Airduct Design: It makes the heat dissipation very well.
- 6. Multiple Options: UK, US, and Universal socket for option.
- 7. Protection: Over current, Over charge, over discharge, over temperature, over voltage, short circuit, recovered output after 30 seconds.



What it powers









Mini CPAP







AC Output: 110V/60Hz or 220V/50Hz,Rated output:120W, Max 200W,surge 2S USB Ports: 2*USB 5V/2.4A, 1*QC3.0(5V/3A,9V/2A,12V/1.5A)

Capacity: 7V/41600mAh(154Wh)
Battery: Li-ion 18650 Battery cell



Specifications:

1. Input: DC19V/2A (By solar panel or adaptor)

2. LED light: Torch, SOS, Emergency

3. Inverter:11* 110V/60Hz or 220V/50Hz

4. AC Raged Output 120W ,Max 200W Surge 2S

5. Power Inverter: Pure sine-wave

6. Capacity: 3.7V/41600mAh

7. CE/FCC/RoHS approved

8. Product size: 230*90*90mm

9. Net Weight: 1.8Kg

TEL: 886-2-2578-8660 FAX: 886-2-2578-8030

7F-4, #21 Section-1, Tunhwa south road, Taipei Taiwan 10557